



May 1999

LMC6484 CMOS Quad Rail-to-Rail Input and Output Operational Amplifier

General Description

The LMC6484 provides a common-mode range that extends to both supply rails. This rail-to-rail performance combined with excellent accuracy, due to a high CMRR, makes it unique among rail-to-rail input amplifiers.

It is ideal for systems, such as data acquisition, that require a large input signal range. The LMC6484 is also an excellent upgrade for circuits using limited common-mode range amplifiers such as the TLC274 and TLC279.

Maximum dynamic signal range is assured in low voltage and single supply systems by the LMC6484's rail-to-rail output swing. The LMC6484's rail-to-rail output swing is guaranteed for loads down to 600Ω.

Guaranteed low voltage characteristics and low power dissipation make the LMC6484 especially well-suited for battery-operated systems.

See the LMC6482 data sheet for a Dual CMOS operational amplifier with these same features.

Features

(Typical unless otherwise noted)


- Rail-to-Rail Input Common-Mode Voltage Range (Guaranteed Over Temperature)
- Rail-to-Rail Output Swing (within 20 mV of supply rail, 100 kΩ load)
- Guaranteed 3V, 5V and 15V Performance
- Excellent CMRR and PSRR: 82 dB
- Ultra Low Input Current: 20 fA
- High Voltage Gain ($R_L = 500 \text{ k}\Omega$): 130 dB
- Specified for 2 kΩ and 600Ω loads

Applications

- Data Acquisition Systems
- Transducer Amplifiers
- Hand-held Analytic Instruments
- Medical Instrumentation
- Active Filter, Peak Detector, Sample and Hold, pH Meter, Current Source
- Improved Replacement for TLC274, TLC279


3V Single Supply Buffer Circuit

Rail-to-Rail Input




DS011714-1

Rail-to-Rail Output



DS011714-3




DS011714-2

LMC6484 CMOS Quad Rail-to-Rail Input and Output Operational Amplifier



Connection Diagram



Ordering Information

| Package | Temperature Range | | NSC Drawing | Transport Media |
|-------------------------|-----------------------------|------------------------------|-------------|-----------------------|
| | Military -55°C to +125°C | Industrial -40°C to +85°C | | |
| 14-pin Molded DIP | LMC6484MN | LMC6484AIN LMC6484IN | N14A | Rail |
| 14-pin Small Outline | | LMC6484AIM LMC6484IM | M14A | Rail Tape and Reel |
| 14-pin Ceramic DIP | LMC6484AMJ/883 | | J14A | Rail |
| 14-pin Ceramic SOIC | LMC6484AMWG/883 | | WG14A | Tray |

Absolute Maximum Ratings (Note 1)

If Military/Aerospace specified devices are required, please contact the National Semiconductor Sales Office/Distributors for availability and specifications.

| | |
|---------------------------------------------------|----------------------------------------------------|
| ESD Tolerance (Note 2) | 2.0 kV |
| Differential Input Voltage | ±Supply Voltage |
| Voltage at Input/Output Pin | (V ⁺) + 0.3V, (V ⁻) – 0.3V |
| Supply Voltage (V ⁺ – V ⁻) | 16V |
| Current at Input Pin (Note 12) | ±5 mA |
| Current at Output Pin (Notes 3, 8) | ±30 mA |
| Current at Power Supply Pin | 40 mA |
| Lead Temp. (Soldering, 10 sec.) | 260°C |

| | |
|-------------------------------|-----------------|
| Storage Temperature Range | –65°C to +150°C |
| Junction Temperature (Note 4) | 150°C |

Operating Ratings (Note 1)

| | |
|---------------------------------------|---------------------------------|
| Supply Voltage | 3.0V ≤ V ⁺ ≤ 15.5V |
| Junction Temperature Range | –55°C ≤ T _J ≤ +125°C |
| LMC6484AM | –40°C ≤ T _J ≤ +85°C |
| LMC6484AI, LMC6484I | |
| Thermal Resistance (θ _{JA}) | |
| N Package, 14-Pin Molded DIP | 70°C/W |
| M Package, 14-Pin Surface Mount | 110°C/W |

DC Electrical Characteristics

Unless otherwise specified, all limits guaranteed for T_J = 25°C, V⁺ = 5V, V⁻ = 0V, V_{CM} = V_O = V⁺/2 and R_L > 1M. **Boldface** limits apply at the temperature extremes.

| Symbol | Parameter | Conditions | Typ (Note 5) | LMC6484AI Limit (Note 6) | LMC6484I Limit (Note 6) | LMC6484M Limit (Note 6) | Units | |
|-------------------|------------------------------------------|-----------------------------------------------------------------------------|----------------------|-----------------------------------------------|-----------------------------------------------|-----------------------------------------------|------------------|-------------|
| V _{OS} | Input Offset Voltage | | 0.110 | 0.750 1.35 | 3.0 3.7 | 3.0 3.8 | mV max | |
| TCV _{OS} | Input Offset Voltage Average Drift | | 1.0 | | | | µV/°C | |
| I _B | Input Current | (Note 13) | 0.02 | 4.0 | 4.0 | 100 | pA max | |
| I _{OS} | Input Offset Current | (Note 13) | 0.01 | 2.0 | 2.0 | 50 | pA max | |
| C _{IN} | Common-Mode Input Capacitance | | 3 | | | | pF | |
| R _{IN} | Input Resistance | | >10 | | | | Tera Ω | |
| CMRR | Common Mode Rejection Ratio | 0V ≤ V _{CM} ≤ 15.0V, V ⁺ = 15V | 82 | 70 67 | 65 62 | 65 60 | dB min | |
| | | 0V ≤ V _{CM} ≤ 5.0V V ⁺ = 5V | 82 | 70 67 | 65 62 | 65 60 | | |
| +PSRR | Positive Power Supply Rejection Ratio | 5V ≤ V ⁺ ≤ 15V, V ⁻ = 0V, V _O = 2.5V | 82 | 70 67 | 65 62 | 65 60 | dB min | |
| -PSRR | Negative Power Supply Rejection Ratio | -5V ≤ V ⁻ ≤ -15V, V ⁺ = 0V, V _O = -2.5V | 82 | 70 67 | 65 62 | 65 60 | dB min | |
| V _{CM} | Input Common-Mode Voltage Range | V ⁺ = 5V and 15V For CMRR ≥ 50 dB | V ⁻ – 0.3 | -0.25 0 | -0.25 0 | -0.25 0 | V max | |
| | | | V ⁺ + 0.3 | V ⁺ + 0.25 V⁺ | V ⁺ + 0.25 V⁺ | V ⁺ + 0.25 V⁺ | V min | |
| A _V | Large Signal Voltage Gain | R _L = 2kΩ (Notes 7, 13) | Sourcing | 666 | 140 84 | 120 72 | 120 60 | V/mV min |
| | | | Sinking | 75 | 35 20 | 35 20 | 35 18 | V/mV min |
| | | R _L = 600Ω (Notes 7, 13) | Sourcing | 300 | 80 48 | 50 30 | 50 25 | V/mV min |
| | | | Sinking | 35 | 20 13 | 15 10 | 15 8 | V/mV min |

DC Electrical Characteristics (Continued)

Unless otherwise specified, all limits guaranteed for $T_J = 25^\circ\text{C}$, $V^+ = 5\text{V}$, $V^- = 0\text{V}$, $V_{\text{CM}} = V_O = V^+/2$ and $R_L > 1\text{M}$. **Boldface** limits apply at the temperature extremes.

| Symbol | Parameter | Conditions | Typ (Note 5) | LMC6484AI Limit (Note 6) | LMC6484I Limit (Note 6) | LMC6484M Limit (Note 6) | Units | | |
|-----------------|---------------------------------------------------|------------------------------------------------------------|----------------------------------------------------|-----------------------------------------|-------------------------------|-------------------------------|-----------|-----------|-----|
| V_O | Output Swing | $V^+ = 5\text{V}$ $R_L = 2\text{ k}\Omega$ to $V^+/2$ | 4.9 | 4.8 | 4.8 | 4.8 | V | | |
| | | | 0.1 | 0.18 | 0.18 | 0.18 | V | | |
| | | $V^+ = 5\text{V}$ $R_L = 600\Omega$ to $V^+/2$ | 4.7 | 4.7 | 4.7 | 4.7 | max | | |
| | | | 0.3 | 0.5 | 0.5 | 0.5 | V | | |
| | | $V^+ = 15\text{V}$ $R_L = 2\text{ k}\Omega$ to $V^+/2$ | 4.5 | 4.24 | 4.24 | 4.24 | min | | |
| | | | 0.65 | 0.65 | 0.65 | 0.65 | max | | |
| | | $V^+ = 15\text{V}$ $R_L = 600\Omega$ to $V^+/2$ | 14.7 | 14.4 | 14.4 | 14.4 | V | | |
| | | | 0.16 | 0.32 | 0.32 | 0.32 | V | | |
| I_{SC} | Output Short Circuit Current $V^+ = 5\text{V}$ | Sourcing, $V_O = 0\text{V}$ | 20 | 16 | 16 | 16 | mA | | |
| | | | 12 | 12 | 12 | 10 | min | | |
| | | Sinking, $V_O = 5\text{V}$ | 15 | 11 | 11 | 11 | mA | | |
| | | | 9.5 | 9.5 | 9.5 | 8.0 | min | | |
| | | I_{SC} | Output Short Circuit Current $V^+ = 15\text{V}$ | Sourcing, $V_O = 0\text{V}$ | 30 | 28 | 28 | 28 | mA |
| | | | | | 22 | 22 | 22 | 20 | min |
| | | | | Sinking, $V_O = 12\text{V}$ (Note 8) | 30 | 30 | 30 | 30 | mA |
| | | | | | 24 | 24 | 24 | 22 | min |
| I_S | Supply Current | All Four Amplifiers $V^+ = +5\text{V}$, $V_O = V^+/2$ | 2.0 | 2.8 | 2.8 | 2.8 | mA | | |
| | | | 3.6 | 3.6 | 3.6 | 3.8 | max | | |
| | | All Four Amplifiers $V^+ = +15\text{V}$, $V_O = V^+/2$ | 2.6 | 3.0 | 3.0 | 3.0 | mA | | |
| | | | 3.8 | 3.8 | 4.0 | max | | | |

AC Electrical Characteristics

Unless otherwise specified, all limits guaranteed for $T_J = 25^\circ\text{C}$, $V^+ = 5\text{V}$, $V^- = 0\text{V}$, $V_{\text{CM}} = V_O = V^+/2$ and $R_L > 1\text{M}$. **Boldface** limits apply at the temperature extremes.

| Symbol | Parameter | Conditions | Typ (Note 5) | LMC6484A Limit (Note 6) | LMC6484I Limit (Note 6) | LMC6484M Limit (Note 6) | Units |
|----------|------------------------------|---------------------------------------------------|-----------------|-------------------------------|-------------------------------|-------------------------------|------------------------|
| SR | Slew Rate | (Note 9) | 1.3 | 1.0 | 0.9 | 0.9 | V/ μs |
| | | | | 0.7 | 0.63 | 0.54 | min |
| GBW | Gain-Bandwidth Product | $V^+ = 15\text{V}$ | 1.5 | | | | MHz |
| ϕ_m | Phase Margin | | 50 | | | | Deg |
| G_m | Gain Margin | | 15 | | | | dB |
| | Amp-to-Amp Isolation | (Note 10) | 150 | | | | dB |
| e_n | Input-Referred Voltage Noise | $f = 1\text{ kHz}$ $V_{\text{CM}} = 1\text{V}$ | 37 | | | | nV/ $\sqrt{\text{Hz}}$ |
| i_n | Input-Referred Current Noise | $f = 1\text{ kHz}$ | 0.03 | | | | pA/ $\sqrt{\text{Hz}}$ |

AC Electrical Characteristics (Continued)

Unless otherwise specified, all limits guaranteed for $T_J = 25^\circ\text{C}$, $V^+ = 5\text{V}$, $V^- = 0\text{V}$, $V_{\text{CM}} = V_O = V^+/2$ and $R_L > 1\text{M}$. **Boldface** limits apply at the temperature extremes.

| Symbol | Parameter | Conditions | Typ (Note 5) | LMC6484A Limit (Note 6) | LMC6484I Limit (Note 6) | LMC6484M Limit (Note 6) | Units |
|--------|---------------------------|------------------------------------------------------------------------------------------------------------------------|-----------------|-------------------------------|-------------------------------|-------------------------------|-------|
| T.H.D. | Total Harmonic Distortion | $f = 1\text{ kHz}$, $A_V = -2$ $R_L = 10\text{ k}\Omega$, $V_O = 4.1\text{ V}_{\text{PP}}$ | 0.01 | | | | % |
| | | $f = 10\text{ kHz}$, $A_V = -2$ $R_L = 10\text{ k}\Omega$, $V_O = 8.5\text{ V}_{\text{PP}}$ $V^+ = 10\text{V}$ | 0.01 | | | | % |

DC Electrical Characteristics

Unless otherwise specified, all limits guaranteed for $T_J = 25^\circ\text{C}$, $V^+ = 3\text{V}$, $V^- = 0\text{V}$, $V_{\text{CM}} = V_O = V^+/2$ and $R_L > 1\text{M}$

| Symbol | Parameter | Conditions | Typ (Note 5) | LMC6484AI Limit (Note 6) | LMC6484I Limit (Note 6) | LMC6484M Limit (Note 6) | Units |
|--------------------------|---------------------------------------|----------------------------------------------------------|-----------------|--------------------------------|-------------------------------|-------------------------------|------------------------------|
| V_{OS} | Input Offset Voltage | | 0.9 | 2.0 2.7 | 3.0 3.7 | 3.0 3.8 | mV max |
| TCV_{OS} | Input Offset Voltage Average Drift | | 2.0 | | | | $\mu\text{V}/^\circ\text{C}$ |
| I_{B} | Input Bias Current | | 0.02 | | | | pA |
| I_{OS} | Input Offset Current | | 0.01 | | | | pA |
| CMRR | Common Mode Rejection Ratio | $0\text{V} \leq V_{\text{CM}} \leq 3\text{V}$ | 74 | 64 | 60 | 60 | dB min |
| PSRR | Power Supply Rejection Ratio | $3\text{V} \leq V^+ \leq 15\text{V}$, $V^- = 0\text{V}$ | 80 | 68 | 60 | 60 | dB min |
| V_{CM} | Input Common-Mode Voltage Range | For CMRR $\geq 50\text{ dB}$ | $V^- - 0.25$ | 0 | 0 | 0 | V max |
| | | | $V^+ + 0.25$ | V^+ | V^+ | V^+ | V min |
| V_O | Output Swing | $R_L = 2\text{ k}\Omega$ to $V^+/2$ | 2.8 | | | | V |
| | | | 0.2 | | | | V |
| | | $R_L = 600\Omega$ to $V^+/2$ | 2.7 | 2.5 | 2.5 | 2.5 | V min |
| | | | 0.37 | 0.6 | 0.6 | 0.6 | V max |
| I_{S} | Supply Current | All Four Amplifiers | 1.65 | 2.5 3.0 | 2.5 3.0 | 2.5 3.2 | mA max |

AC Electrical Characteristics

Unless otherwise specified, $V^+ = 3\text{V}$, $V^- = 0\text{V}$, $V_{\text{CM}} = V_O = V^+/2$ and $R_L > 1\text{M}$

| Symbol | Parameter | Conditions | Typ (Note 5) | LMC6484AI Limit (Note 6) | LMC6484I Limit (Note 6) | LMC6484M Limit (Note 6) | Units |
|--------|---------------------------|------------------------------------------------------------------------------------------------|-----------------|--------------------------------|-------------------------------|-------------------------------|------------------|
| SR | Slew Rate | (Note 11) | 0.9 | | | | V/ μs |
| GBW | Gain-Bandwidth Product | | 1.0 | | | | MHz |
| T.H.D. | Total Harmonic Distortion | $f = 10\text{ kHz}$, $A_V = -2$ $R_L = 10\text{ k}\Omega$, $V_O = 2\text{ V}_{\text{PP}}$ | 0.01 | | | | % |

Note 1: Absolute Maximum Ratings indicate limits beyond which damage to the device may occur. Operating Ratings indicate conditions for which the device is intended to be functional, but specific performance is not guaranteed. For guaranteed specifications and the test conditions, see the Electrical Characteristics.

Note 2: Human body model, 1.5 k Ω in series with 100 pF. All pins rated per method 3015.6 of MIL-STD-883. This is a class 2 device rating.

AC Electrical Characteristics (Continued)

Note 3: Applies to both single supply and split-supply operation. Continuous short circuit operation at elevated ambient temperature can result in exceeding the maximum allowed junction temperature of 150°C. Output currents in excess of ±30 mA over long term may adversely affect reliability.

Note 4: The maximum power dissipation is a function of $T_{J(max)}$, θ_{JA} , and T_A . The maximum allowable power dissipation at any ambient temperature is $P_D = (T_{J(max)} - T_A)/\theta_{JA}$. All numbers apply for packages soldered directly into a PC board.

Note 5: Typical Values represent the most likely parametric norm.

Note 6: All limits are guaranteed by testing or statistical analysis.

Note 7: $V^+ = 15V$, $V_{CM} = 7.5V$ and R_L connected to 7.5V. For Sourcing tests, $7.5V \leq V_O \leq 11.5V$. For Sinking tests, $3.5V \leq V_O \leq 7.5V$.

Note 8: Do not short circuit output to V^+ , when V^+ is greater than 13V or reliability will be adversely affected.

Note 9: $V^+ = 15V$. Connected as Voltage Follower with 10V step input. Number specified is the slower of either the positive or negative slew rates.

Note 10: Input referred, $V^+ = 15V$ and $R_L = 100\text{ k}\Omega$ connected to 7.5V. Each amp excited in turn with 1 kHz to produce $V_O = 12\text{ V}_{PP}$.

Note 11: Connected as Voltage Follower with 2V step input. Number specified is the slower of either the positive or negative slew rates.


Note 12: Limiting input pin current is only necessary for input voltages that exceed absolute maximum input voltage ratings.

Note 13: Guaranteed limits are dictated by tester limitations and not device performance. Actual performance is reflected in the typical value.


Note 14: For guaranteed Military Temperature Range parameters see RETSMC6484X.

Typical Performance Characteristics $V_S = +15V$, Single Supply, $T_A = 25^\circ\text{C}$ unless otherwise specified


Supply Current vs Supply Voltage




Input Current vs Temperature




Sourcing Current vs Output Voltage




Sourcing Current vs Output Voltage



Sourcing Current vs Output Voltage




Sinking Current vs Output Voltage




Typical Performance Characteristics $V_S = +15V$, Single Supply, $T_A = 25^\circ C$ unless otherwise specified (Continued)


Sinking Current vs Output Voltage




Sinking Current vs Output Voltage




Output Voltage Swing vs Supply Voltage




Input Voltage Noise vs Frequency




Input Voltage Noise vs Input Voltage




Input Voltage Noise vs Input Voltage



Input Voltage Noise vs Input Voltage




Crosstalk Rejection vs Frequency




Typical Performance Characteristics $V_S = +15V$, Single Supply, $T_A = 25^\circ C$ unless otherwise specified (Continued)


Crosstalk Rejection vs Frequency




Positive PSRR vs Frequency




Negative PSRR vs Frequency




CMRR vs Frequency




CMRR vs Input Voltage




CMRR vs Input Voltage




CMRR vs Input Voltage



ΔV_{OS} vs CMR




ΔV_{OS} vs CMR




Typical Performance Characteristics $V_S = +15V$, Single Supply, $T_A = 25^\circ C$ unless otherwise specified (Continued)


Input Voltage vs Output Voltage




Input Voltage vs Output Voltage




Open Loop Frequency Response




Open Loop Frequency Response




Open Loop Frequency Response vs Temperature




Maximum Output Swing vs Frequency




Gain and Phase vs Capacitive Load



Gain and Phase vs Capacitive Load




Open Loop Output Impedance vs Frequency




Typical Performance Characteristics $V_S = +15V$, Single Supply, $T_A = 25^\circ C$ unless otherwise specified (Continued)


Open Loop Output Impedance vs Frequency




Slew Rate vs Supply Voltage




Non-Inverting Large Signal Pulse Response




Non-Inverting Large Signal Pulse Response




Non-Inverting Large Signal Pulse Response




Non-Inverting Small Signal Pulse Response




Non-Inverting Small Signal Pulse Response



Non-Inverting Small Signal Pulse Response




Inverting Large Signal Pulse Response




Typical Performance Characteristics $V_S = +15V$, Single Supply, $T_A = 25^\circ C$ unless otherwise specified (Continued)


Inverting Large Signal Pulse Response




Inverting Large Signal Pulse Response




Inverting Small Signal Pulse Response




Inverting Small Signal Pulse Response




Inverting Small Signal Pulse Response




Stability vs Capacitive Load




Stability vs Capacitive Load



Stability vs Capacitive Load




Stability vs Capacitive Load




Typical Performance Characteristics $V_S = +15V$, Single Supply, $T_A = 25^\circ C$ unless otherwise specified (Continued)

Stability vs Capacitive Load



Stability vs Capacitive Load



Application Information

1.0 Amplifier Topology

The LMC6484 incorporates specially designed wide-compliance range current mirrors and the body effect to extend input common mode range to each supply rail. Complementary paralleled differential input stages, like the type used in other CMOS and bipolar rail-to-rail input amplifiers, were not used because of their inherent accuracy problems due to CMRR, cross-over distortion, and open-loop gain variation.

The LMC6484's input stage design is complemented by an output stage capable of rail-to-rail output swing even when driving a large load. Rail-to-rail output swing is obtained by taking the output directly from the internal integrator instead of an output buffer stage.

2.0 Input Common-Mode Voltage Range

Unlike Bi-FET amplifier designs, the LMC6484 does not exhibit phase inversion when an input voltage exceeds the negative supply voltage. Figure 1 shows an input voltage exceeding both supplies with no resulting phase inversion on the output.




FIGURE 1. An Input Voltage Signal Exceeds the LMC6484 Power Supply Voltages with No Output Phase Inversion

The absolute maximum input voltage is 300 mV beyond either supply rail at room temperature. Voltages greatly ex-

ceeding this absolute maximum rating, as in Figure 2, can cause excessive current to flow in or out of the input pins possibly affecting reliability.




FIGURE 2. A $\pm 7.5V$ Input Signal Greatly Exceeds the 3V Supply in Figure 3 Causing No Phase Inversion Due to R_I

Applications that exceed this rating must externally limit the maximum input current to ± 5 mA with an input resistor as shown in Figure 3.




FIGURE 3. R_I Input Current Protection for Voltages Exceeding the Supply Voltage

3.0 Rail-To-Rail Output

The approximated output resistance of the LMC6484 is 180 Ω sourcing and 130 Ω sinking at $V_S = 3V$ and 110 Ω sourcing and 83 Ω sinking at $V_S = 5V$. Using the calculated output resistance, maximum output voltage swing can be estimated as a function of load.

4.0 Capacitive Load Tolerance

The LMC6484 can typically directly drive a 100 pF load with $V_S = 15V$ at unity gain without oscillating. The unity gain follower is the most sensitive configuration. Direct capacitive

Application Information (Continued)

loading reduces the phase margin of op-amps. The combination of the op-amp's output impedance and the capacitive load induces phase lag. This results in either an underdamped pulse response or oscillation.

Capacitive load compensation can be accomplished using resistive isolation as shown in *Figure 4*. This simple technique is useful for isolating the capacitive input of multiplexers and A/D converters.




FIGURE 4. Resistive Isolation of a 330 pF Capacitive Load




FIGURE 5. Pulse Response of the LMC6484 Circuit in Figure 4

Improved frequency response is achieved by indirectly driving capacitive loads as shown in *Figure 6*.




FIGURE 6. LMC6484 Non-Inverting Amplifier, Compensated to Handle a 330 pF Capacitive Load

R1 and C1 serve to counteract the loss of phase margin by feeding forward the high frequency component of the output signal back to the amplifier's inverting input, thereby preserving phase margin in the overall feedback loop. The values of R1 and C1 are experimentally determined for the desired pulse response. The resulting pulse response can be seen in *Figure 7*.




FIGURE 7. Pulse Response of LMC6484 Circuit in Figure 6

5.0 Compensating for Input Capacitance

It is quite common to use large values of feedback resistance with amplifiers that have ultra-low input current, like the LMC6484. Large feedback resistors can react with small values of input capacitance due to transducers, photodiodes, and circuit board parasitics to reduce phase margins.




FIGURE 8. Canceling the Effect of Input Capacitance

The effect of input capacitance can be compensated for by adding a feedback capacitor. The feedback capacitor (as in *Figure 8*), C_f , is first estimated by:

$$\frac{1}{2\pi R_1 C_{IN}} \geq \frac{1}{2\pi R_2 C_f}$$

or

$$R_1 C_{IN} \leq R_2 C_f$$

which typically provides significant overcompensation.

Printed circuit board stray capacitance may be larger or smaller than that of a breadboard, so the actual optimum value for C_f may be different. The values of C_f should be checked on the actual circuit. (Refer to the LMC660 quad CMOS amplifier data sheet for a more detailed discussion.)

6.0 Printed-Circuit-Board Layout for High-Impedance Work

It is generally recognized that any circuit which must operate with less than 1000 pA of leakage current requires special layout of the PC board. when one wishes to take advantage

Application Information (Continued)

of the ultra-low input current of the LMC6484, typically less than 20 fA, it is essential to have an excellent layout. Fortunately, the techniques of obtaining low leakages are quite simple. First, the user must not ignore the surface leakage of the PC board, even though it may sometimes appear acceptably low, because under conditions of high humidity or dust or contamination, the surface leakage will be appreciable.

To minimize the effect of any surface leakage, lay out a ring of foil completely surrounding the LMC6484's inputs and the terminals of capacitors, diodes, conductors, resistors, relay terminals, etc. connected to the op-amp's inputs, as in *Figure 9*. To have a significant effect, guard rings should be placed in both the top and bottom of the PC board. This PC foil must then be connected to a voltage which is at the same voltage as the amplifier inputs, since no leakage current can flow between two points at the same potential. For example, a PC board trace-to-pad resistance of $10^{12}\Omega$, which is normally considered a very large resistance, could leak 5 pA if the trace were a 5V bus adjacent to the pad of the input. This would cause a 250 times degradation from the LMC6484's actual performance. However, if a guard ring is held within 5 mV of the inputs, then even a resistance of $10^{11}\Omega$ would cause only 0.05 pA of leakage current. See *Figure 10* for typical connections of guard rings for standard op-amp configurations.







FIGURE 9. Example of Guard Ring in P.C. Board Layout



Inverting Amplifier




Non-Inverting Amplifier



Follower

FIGURE 10. Typical Connections of Guard Rings

The designer should be aware that when it is inappropriate to lay out a PC board for the sake of just a few circuits, there is another technique which is even better than a guard ring on a PC board: Don't insert the amplifier's input pin into the board at all, but bend it up in the air and use only air as an insulator. Air is an excellent insulator. In this case you may have to forego some of the advantages of PC board construction, but the advantages are sometimes well worth the effort of using point-to-point up-in-the-air wiring. See *Figure 11*.




(Input pins are lifted out of PC board and soldered directly to components. All other pins connected to PC board.)

FIGURE 11. Air Wiring

Application Information (Continued)

7.0 Offset Voltage Adjustment


Offset voltage adjustment circuits are illustrated in *Figures 13, 14*. Large value resistances and potentiometers are used to reduce power consumption while providing typically ± 2.5 mV of adjustment range, referred to the input, for both configurations with $V_S = \pm 5V$.



$$\frac{V_{OUT}}{V_{IN}} = -\frac{R4}{R3}$$

DS011714-25

FIGURE 12. Inverting Configuration Offset Voltage Adjustment



$$\frac{V_{OUT}}{V_{IN}} = 1 + \frac{R4}{R3} ; R2 \ll R3$$

DS011714-26

FIGURE 13. Non-Inverting Configuration Offset Voltage Adjustment

8.0 Upgrading Applications

The LMC6484 quads and LMC6482 duals have industry standard pin outs to retrofit existing applications. System performance can be greatly increased by the LMC6484's features. The key benefit of designing in the LMC6484 is increased linear signal range. Most op-amps have limited input common mode ranges. Signals that exceed this range generate a non-linear output response that persists long after the input signal returns to the common mode range.

Linear signal range is vital in applications such as filters where signal peaking can exceed input common mode ranges resulting in output phase inversion or severe distortion.

9.0 Data Acquisition Systems

Low power, single supply data acquisition system solutions are provided by buffering the ADC12038 with the LMC6484 (*Figure 14*). Capable of using the full supply range, the LMC6484 does not require input signals to be scaled down to meet limited common mode voltage ranges. The LMC6484 CMRR of 82 dB maintains integral linearity of a 12-bit data acquisition system to ± 0.325 LSB. Other rail-to-rail input amplifiers with only 50 dB of CMRR will degrade the accuracy of the data acquisition system to only 8 bits.

Application Information (Continued)




FIGURE 14. Operating from the same Supply Voltage, the LMC6484 buffers the ADC12038 maintaining excellent accuracy

10.0 Instrumentation Circuits

The LMC6484 has the high input impedance, large common-mode range and high CMRR needed for designing instrumentation circuits. Instrumentation circuits designed with the LMC6484 can reject a larger range of common-mode signals than most in-amps. This makes instrumentation circuits designed with the LMC6484 an excellent choice for noisy or industrial environments. Other appli-

cations that benefit from these features include analytic medical instruments, magnetic field detectors, gas detectors, and silicon-based transducers.

A small valued potentiometer is used in series with R_G to set the differential gain of the 3 op-amp instrumentation circuit in *Figure 15*. This combination is used instead of one large valued potentiometer to increase gain trim accuracy and reduce error due to vibration.





FIGURE 15. Low Power 3 Op-Amp Instrumentation Amplifier

A 2 op-amp instrumentation amplifier designed for a gain of 100 is shown in *Figure 16*. Low sensitivity trimming is made

Application Information (Continued)

for offset voltage, CMRR and gain. Low cost and low power consumption are the main advantages of this two op-amp circuit.

Higher frequency and larger common-mode range applications are best facilitated by a three op-amp instrumentation amplifier.



DS011714-30

FIGURE 16. Low-Power Two-Op-Amp Instrumentation Amplifier

11.0 Spice Macromodel


A spice macromodel is available for the LMC6484. This model includes accurate simulation of:

- input common-mode voltage range
- frequency and transient response
- GBW dependence on loading conditions
- quiescent and dynamic supply current
- output swing dependence on loading conditions

and many more characteristics as listed on the macromodel disk.


Contact your local National Semiconductor sales office to obtain an operational amplifier spice model library disk.

Typical Single-Supply Applications



DS011714-31


FIGURE 17. Half-Wave Rectifier with Input Current Protection (R_I)



DS011714-32

FIGURE 18. Half-Wave Rectifier Waveform


The circuit in Figure 17 use a single supply to half wave rectify a sinusoid centered about ground. R_I limits current into the amplifier caused by the input voltage exceeding the supply voltage. Full wave rectification is provided by the circuit in Figure 19.



DS011714-33


FIGURE 19. Full Wave Rectifier with Input Current Protection (R_I)

Typical Single-Supply Applications (Continued)




DS011714-34

FIGURE 20. Full Wave Rectifier Waveform



DS011714-35


FIGURE 21. Large Compliance Range Current Source



DS011714-36

FIGURE 22. Positive Supply Current Sense


Typical Single-Supply Applications (Continued)



DS011714-37

FIGURE 23. Low Voltage Peak Detector with Rail-to-Rail Peak Capture Range


In *Figure 23* dielectric absorption and leakage is minimized by using a polystyrene or polyethylene hold capacitor. The droop rate is primarily determined by the value of C_H and diode leakage current. The ultra-low input current of the LMC6484 has a negligible effect on droop.



DS011714-38

FIGURE 24. Rail-to-Rail Sample and Hold

The LMC6484's high CMRR (85 dB) allows excellent accuracy throughout the circuit's rail-to-rail dynamic capture range.




DS011714-27

$$R1 = R2, C1 = C2; f = \frac{1}{2\pi R1C1}; DF = \frac{1}{2} \sqrt{\frac{C2}{C1}} \sqrt{\frac{R2}{R1}}$$

FIGURE 25. Rail-to-Rail Single Supply Low Pass Filter

The low pass filter circuit in *Figure 25* can be used as an anti-aliasing filter with the same voltage supply as the A/D converter. Filter designs can also take advantage of the LMC6484 ultra-low input current. The ultra-low input current yields negligible offset error even when large value resistors are used. This in turn allows the use of smaller valued capacitors which take less board space and cost less.




Physical Dimensions inches (millimeters) unless otherwise noted



14-Pin Ceramic Dual-In-Line Package
 Order Number LMC6484AMJ/883, LMC6484AMWG/883
 NS Package Number J14A, WG14A

J14A (REV G)


Physical Dimensions inches (millimeters) unless otherwise noted (Continued)



M14A (REV 11)

14-Pin Small Outline
Order Package Number LMC6484AIM or LMC6484IM
NS Package Number M14A

Physical Dimensions inches (millimeters) unless otherwise noted (Continued)



14-Pin Molded DIP
Order Package Number LMC6484AIN, LMC6484IN or LMC6484MN
NS Package Number N14A

LIFE SUPPORT POLICY

NATIONAL'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT AND GENERAL COUNSEL OF NATIONAL SEMICONDUCTOR CORPORATION. As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury to the user.
2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

National Semiconductor Corporation
Americas
Tel: 1-800-272-9959
Fax: 1-800-737-7018
Email: support@nsc.com
www.national.com

National Semiconductor Europe
Fax: +49 (0) 1 80-530 85 86
Email: europe.support@nsc.com
Deutsch Tel: +49 (0) 1 80-530 85 85
English Tel: +49 (0) 1 80-532 78 32
Français Tel: +49 (0) 1 80-532 93 58
Italiano Tel: +49 (0) 1 80-534 16 80

National Semiconductor Asia Pacific Customer Response Group
Tel: 65-2544466
Fax: 65-2504466
Email: sea.support@nsc.com

National Semiconductor Japan Ltd.
Tel: 81-3-5639-7560
Fax: 81-3-5639-7507