

KA3084D

2-Phase BLDC Motor Driver


Features

- Drives the BLDC motor using 2 hall sensors.
- 2-phase, full-wave drive method
- Built-in thermal shutdown (TSD) circuit
- Controls the motor speed through voltage
- Built-in bandgap circuit
- Built-in frequency Generator (FG) & Phase Generator (PG) amplifier & comparator.

Description

The KA3084D is a monolithic integrated circuit, and it is suitable for drum motor driver of VCR system.

22-SOP-300




Target Applications

- Video cassette recorder(VCR) cylinder (drum) motor
- Other 2-phase BLDC motor

Ordering Information

Device	Package	Operating Temp.
KA3084D	22-SOP-300	-25°C ~ +75°C
KA3084DTF	22-SOP-300	-25°C ~ +75°C


Pin Assignments



Pin Definitions

Pine Number	Pin Name	I/O	Pin Function Description
1	GND (Signal)	-	Ground (Signal)
2	VCC2	-	Power supply 2
3	OUT2P	O	Output drive 2(P)
4	GND2 (Power)	-	Power ground 2
5	OUT2N	O	Output drive 2(N)
6	OUT1P	O	Power supply 1(P)
7	GND1 (Power)	-	Power ground 1
8	OUT1N	O	Output drive 1(N)
9	VCC1	-	Power supply 1
10	H1P	I	Hall signal input 1P
11	H1N	I	Hall signal input 1N
12	H2P	I	Hall signal input 2P
13	H2N	I	Hall signal input 2N
14	VCTL	I	Voltage control (Motor speed control)
15	PGOUT	O	Phase generator output
16	PGAMPOUT	O	Phase generator amp. output
17	PGIN	I	Phase generator input
18	VREG	O	Regurated voltage
19	FGIN	I	Frequency generator input
20	V25	I/O	Reference voltage
21	FGAMPOUT	O	Frequency generator amp. output
22	FGOUT	O	Frequency generator output

Internal Block Diagram



Equivalent Circuits

Description	Pin No.	Internal circuit
VCTL	14	
Motor output	3, 5, 6, 8	
Hall input	10, 11, 12, 13	

Equivalent Circuits (Continued)

Description	Pin No.	Internal circuit
PG, FG amplifier	16, 17 19, 21	
PG, FG hysteresis amplifier	3, 5, 6, 8	


Absolute Maximum Ratings (Ta=25°C)

Parameter	Symbol	Value	Unit	Remark
Supply voltage	VCCmax	18	V	-
Maxium output current	IOmax	1.0 ^{note1}	A	-
VREG output current	I _{REG} max	30	mA	-
Power dissipation	P _d	1 ^{note2}	W	No heat sink
Operating temperature	T _{OPR}	-25 ~ +75	°C	-
Storage temperature	T _{STG}	-45 ~ +125	°C	-

Notes:

1. Duty 1 / 100, pulse width 500μs
2. 1) When mounted on glass epoxy PCB (76.2 × 114 × 1.57mm)
2) Power dissipation reduces 8.0mW / °C for using above Ta=25°C. (Without heat-sink)
3) Do not exceed P_d and SOA(Safe Operating Area).

Power Dissipation Curve




Recommended Operating Conditions (Ta = 25°C)

Parameter	Symbol	Min.	Typ.	Max	Units
Operating supply voltage	VCC	8	12	16	V

Electrical Characteristics

(Ta=25°C, VCC=12V, unless otherwise specified)

Parameter	Symbol	Condition	Min.	Typ.	Max.	Units
FULL CIRCUIT						
Quiescent current	I _Q	V _{CC} =12V	-	8.5	13	mA
VOLTAGE REGULATOR						
Regulated voltage	V _{REG}	V _{CC} =12V	4.6	5.0	5.4	V
Regulated voltage	V _{REG}	V _{CC} =12V, I _{REG} =-20mA	4.6	5.0	5.4	V
HALL INPUT						
Hall minimum input level ^{note}	V _{INH}	-	50	-	-	mVp-p
Hall bias current	I _{BH}	V _{CTL} =2.0V, Hall=2.5V	-	0.25	2.0	μA
OUTPUT DIRVE						
Output saturation voltage (Upper)	V _{SU}	V _{CTL} =4.5V	-	1.3	2.0	V
Output saturation voltage (Lower)	V _{SL}	V _{CTL} =4.5V	-	2.0	2.0	V
Output current A	I _{OUTA}	V _{H1P} =2.6V V _{H1N} =2.4V, V _{CTL} =3.5V	500	700	900	mA
Output current B	I _{OUTB}	V _{H2P} =2.6V V _{H2N} =2.4V, V _{CTL} =2.5V	500	700	900	mA
VOLTAGE CONTROL						
V _{CTL} reference voltage ^{note}	V ₂₅	0.48 × V _{REG}	2.0	2.3	2.5	V
V _{CTL} input range ^{note}	V _{CTL}	-	0	-	V _{REG}	V
V _{CTL} offset range	V _{OFF}	V _{CTL} =0 ~ V _{CTL}	-150	0	+150	mV
V _{CTL} input bias current	I _{VCTL}	V _{CTL} =2.5V	-	1.0	6.0	μA
Voltage control gain	G _M	V _{CTL} =2.8V, 3.3V ΔI _O / ΔV _{CTL} V _{H1P} =2.6V, V _{H1N} =2.4V 	0.38	0.55	0.64	A / V

Notes:

The note in the chart means items calculated and approved in design not the items proven by actual test result.

Electrical Characteristics (Continued)

(Ta=25°C, VCC=12V, unless otherwise specified)

Parameter	Symbol	Condition	Min.	Typ.	Max.	Units
FULL CIRCUIT						
Shutdown temperature ^{note}	TSD	-	130	160	-	°C
Temperature hysteresis ^{note}	THYS	-	-	30	-	°C
FG / PG AMP						
Input offset voltage	VOFS	-	-	0	± 8	mV
Input current	IAMPIN	VIN=2.5V	-	0.2	2.0	μA
Open loop gain ^{note}	GA	VCC=12V, Signal=500Hz	65	70	-	dB
Output high voltage	VOHA	VIN=2.0V	VREG -1.48	VREG -0.74	-	V
Output low voltage	VOLA	VIN=2.7	-	0.85	1.45	V
COMPARATOR (HYSTERESIS)						
Hysteresis level	VHYS	-	±130	±165	±200	mV
Output low voltage	VOLHYS	VIN=2.0V	-	0.12	0.32	V
Output pull-up resistance	VBHYS	-	7.0	10	13	kΩ

Notes:

The note in the chart means items calculated and approved in design not the items proven by actual test result.

Application Informations

1. A DIAGRAM SUMMARIZING THE ENTIRE SYSTEM




Figure 1.

Figure 1 is a conceptual diagram of the KA3084D. It shows that it turns on or off depending on the signal of the hall sensor used for sensing the rotor position of motor.

The AMP, GM (Feedback) and output blocks are circuits used to determine current gain of KA3084D.

Furthermore, HallIN represents the hall signal switch.

It supplies stable bias to each VREG block. The TSD block is a thermal shutdown circuit that protects the IC during an high temperature inside the IC.

Moreover, FG. and PG. blocks output individual signals generated in the motor using the amplifier and comparator.

These signals transmit motor speed and position data to controller of external servo etc. for their control.

2. CURRENT CONTROL

Figure 2 simplifies figure 1.

The supplied I_O current drives the motor and the I_c current controls the motor speed.

Figure 3 is a graph of I_{CTL} vs. I_O .




Figure 2.




Figure 3.

3. VOLTAGE CONTROL

Even though KA3084D command uses I_c to control the magnitude of I_O , it can also use voltage. KA3084D mainly uses voltage control and has option to use current control.




Figure 4.

Figure 4 shows the principle of the voltage control.

The V_{CTL} is the motor speed control voltage, and the I_{CTL} is converted to current through the V / I converter.

Figure 5 shows the graph of V_{CTL} vs. I_O .






Figure 5.


Typical Performance Characteristics




1.VCC vs VREG




2.Temp. vs VREG




3.VCC vs ICC



4.VCC vs GM1




5.VCC vs IOA




6.VCC vs IOB

Test Circuits



Typical Application Circuits



DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS.

LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT OF FAIRCHILD SEMICONDUCTOR INTERNATIONAL. As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury of the user.
2. A critical component in any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.