

REVISIONS			DOC. NO. SPC-F004 * Effective: 7/8/02 * DCP No: 1398					
DCP #	REV	DESCRIPTION	DRAWN	DATE	CHECKD	DATE	APPRVD	DATE
1740	Α	RELEASED	JWM	9/16/04	SF	9/16/04	JC	9/16/04



## **FEATURES**

- 3 ¾ Digit LCD, 3999 Count, 63mm x 31mm
- Auto/ manual ranging selector
- Overmoulded cases
- Diode, Continuity and Data hold
- Display Backlight
- Capacitance measurement
- Temperature measurement
- Frequency measurement
- Min/Max, Relative mode
- 1-Year Warranty
- Meets IEC 1010, 1000V CAT II, 600V CAT III
- CE Compliant
- Fused 10A range
- Relative Mode
- Full Icon Display
- Low Battery Display
- Sleep Mode
- Input Impedance for DCV: Approx 10MΩ
- Power: 9V Battery (6F22) Included
- Size: 177mm x 85mm x 40mm
- Weight: 340g
- Includes: Test Leads, Manual, Test Clip,
  Point Contact Temperature Probe

Function	Range	Accuracy
DC Voltage	400mV, 4V, 40V, 400V, 1000V	±(0.8%+1)
AC Voltage	4V, 40V, 400V, 750V	±(1%+5)
DC Current	400 μ A, 4000 μ A, 40mA, 400mA, 4A, 10A	±(1%+2)
AC Current	400 μ A, 4000 μ A, 40mA, 400mA, 4A, 10A	±(1.5%+5)
Resistance	400 $\Omega$ , 4k $\Omega$ , 40k $\Omega$ , 400k $\Omega$ , 4Μ $\Omega$ , 40Μ $\Omega$	±(1%+2)
Capacitance	40nF, 400nF, 4μF, 40μF, 100μF	±(3%+5)
Frequency	10Hz ~ 10MHz	±(0.1%+3)
Duty Cycle	0.1% ~ 99.9%	NA
Termperature °C	-40°C ~ 1000°C	±(1%+3)

SPC-F004.DWG

TOLERANCES: DRAWN BY:		DATE:	DRAW	DRAWING TITLE:					
UNLESS OTHERWISE	Jeff McVicker	9/16/04		Advanced	Autoranging Dig	ital N	Multimeter		
SPECIFIED,	CHECKED BY:	DATE:	SIZE	DWG. NO.		ELEC	TRONIC FILE	REV	
DIMENSIONS ARE FOR REFERENCE	Steve Feiwell	9/16/04	Al	72-7740		02J5541.dwg		A	
PURPOSES ONLY.	APPROVED BY:	DATE:							
	John Cole	9/15/04	SCALE	E: NTS	U.O.M.: INCHES [mm]		SHEET: 1 OF	· 1	

ALL RIGHTS RESERVED. NO PORTION OF THIS PUBLICATION, WHETHER IN WHOLE OR IN PART CAN BE REPRODUCED WITHOUT THE EXPRESS WRITTEN CONSENT OF SPC TECHNOLOGY. DISCLAIMER: ALL STATEMENTS AND TECHNICAL INFORMATION CONTAINED HEREIN ARE BASED UPON INFORMATION AND/OR TESTS WE BELIEVE TO BE ACCURATE AND RELIABLE. SINCE CONDITIONS OF USE ARE BEYOND OUR CONTROL, THE USER SHALL DETERMINE THE SUITABILITY OF THE PRODUCT FOR THE INTENDED USE AND ASSUME ALL RISK AND LIABILITY WHATSOEVER IN CONNECTION THEREWITH.