# **BC Pro UPS System**

### Standby UPS System



#### Model #: BCPRO1400

- 1400VA standby, tower UPS system
- Offers battery derived AC output during blackouts and brownouts starting at 99V
- 6 protected AC outlets (NEMA 5-15R)
- USB communications port and cabling for use with free PowerAlert monitoring software
- \$200,000 Ultimate Lifetime Insurance (USA & Canada only)

#### **DESCRIPTION**

Tripp Lite's BCPRO1400 standby UPS system offers surge suppression and long lasting battery support for personal computers, internetworking equipment and other sensitive electronics. UPS inverter and auto-transfer circuits maintain battery derived AC output during power failures and brownouts so that connected equipment can be safely shutdown without data loss. Includes 6 battery supported AC outlets. USB monitoring port enables optional unattended system shutdown in the case of extended power failure, cable included. PowerAlert UPS monitoring and shutdown software available via free download from www.tripplite.com. Built-in audible alarm and 5 front panel LEDs indicate line power, battery power, low/high input voltage detected, overload and battery low/replace status. 1400VA / 940 watt power handling ability supports entry-level PCs, network workstations, point-of-sale equipment, small business phone systems, audio/video equipment and home theater systems. Offers 8 minutes battery runtime with a full load of 1400VA and 24 minutes with a half load of 700VA. Offers up to 75 minutes runtime with a single desktop computer and 15 inch monitor. Supports user battery replacement via built-in access panel. 2 year warranty. \$200,000 connected equipment insurance (USA & Canada only).

#### **KEY BUYING POINTS**

- BCPRO1400 standby UPS system offers battery support during blackouts and brownouts, plus AC line surge suppression
- Maintains user productivity during utility power problems enabling a safe system shutdown without data loss
- Supports a max load of 1400VA/940 watts for 8 minutes
- Supports a half load of 700VA/470 watts for 24 minutes
- Offers extended runtime operation of up to 75 minutes when used with a single desktop PC and 15 inch monitor
- Supplies battery derived AC output during brownouts starting at 99 volts
- Attractive gray small footprint upright tower configuration
- Includes 6 battery supported NEMA 5-15R output receptacles, 6 foot AC line cord (NEMA 5-15P input connection)
- Built-in USB port enables unattended shutdown without data loss during extended power failures, includes cable
- Communications port supports on battery, low battery and power restored messaging plus additional data regarding AC line voltage and battery charge level
- PowerAlert UPS monitoring and shutdown software available via free download from http://www.tripplite.com
- Supports Tripp Lite's WatchDog software application to restore unresponsive programs by automatically restarting them and rebooting completely locked computers by automatically switching UPS power off and back on again
- Two front panel switches support power off/on control, alarm cancel and UPS self test functions
- Built-in audible alarm and 5 front panel LEDs indicate line power, battery power, battery low/replace, low/high input voltage detected and overload status
- 1400VA power handling ability supports a variety of computer, internetworking, telecom and consumer electronics equipment
- Supports hot swappable user battery replacement via built-in access panel
- Compatible with 120V / 60Hz applications
- UL1778 listed (USA), cUL (Canada), NOM (Mexico), FCC Class B
- 2 year manufacturers warranty
- \$200,000 connected equipment insurance (USA & Canada only)

## TYPICAL APPLICATIONS

• Personal computers, network workstations, mid-size & large business telephone/voicemail systems, home-office workstations, small-

## **OPTIONS & ACCESSORIES**

• Dataline protectors: <u>DNET1</u> <u>DTEL2</u>, <u>DCATV</u>

• Wallmount Bracket: **UPSWM** 

• USB Hubs-accessories: <u>U202-004-R</u>, <u>U205-004-R</u>, <u>U022-010</u>

• WatchDog Software: WATCHDOGSW

• Circuit Tester: CT120

• Extended warranties: 3 Year WEXT3-BCPRO, 5 Year WEXT5-BCPRO

## **PACKAGE INCLUDES**

- BCPRO1400 UPS System
- USB Cable
- Warranty information
- Instruction manual

## **COMPLETE SPECIFICATIONS**

SYSTEM OVERVIEW		
System overview:	Standby tower UPS protects PCs, network workstations and other sensitive electronic equipment from blackouts, surges and line noise. Maintains AC output during blackouts and brownouts starting at 99V. Includes USB port, complete cabling and front panel LED indicators. PowerAlert monitoring software available via free download.	
Voltage compatibility:	120V AC	
Frequency compatibility:	60Hz	
OUTPUT		
Output volt amp capacity (VA):	1400	
Output watt capacity (watts):	940	
Output nominal voltage:	120V AC	
Output voltage regulation:	BATTERY MODE: PWM sine wave output 115V +/-5%	
Output frequency regulation:	LINE MODE: Passes line frequency of 60Hz +/-10% BATTERY MODE: Inverter output regulated to 60Hz +/-0.5Hz	
Outlet quantity / type:	6 NEMA 5-15R	
INPUT		
Maximum input amps:	9.2 amps / 1030 watts	
Input connection type:	NEMA 5-15P	
Input cord length:	6 ft., 14 gauge	
Recommended electrical service:	15A 120V	
BATTERY		
Full load runtime:	8 minutes (1400VA)	
Half load runtime:	24 minutes (700VA)	
DC system voltage:	36 VDC	
Typical battery lifespan:	3-6 years, depending on usage	
Battery recharge rate:	2-4 hours to 90%	
LEDS ALARMS & SWITCHES		

Front panel LEDs:	5 front panel LEDs indicate line power status, battery power status, battery low/replace status, low/high input voltage detected and overload status
Alarms:	Audible alarm with 15 second delay sounds to indicate loss of utility power. Alarm can be silenced by pressing front panel alarm cancel button. Once silenced, alarm will re-sound when approximately 2 minutes runtime remain.
Switches:	Includes 2 front panel switches—one main on/off power switch and one dual function "alarm cancel" / "self test" button
SURGE / NOISE SUPPRESSION	
AC surge suppression:	1800 joules
AC suppression response time:	Instantaneous
EMI / RFI AC noise suppression:	Yes
PHYSICAL	
Shipping weight (lbs):	40
Shipping weight (kg):	18.2
Unit weight (lbs):	36.4
Unit weight (kg):	16.5
Unit Dimensions (HWD/in):	12.75 x 7.5 x 9
Unit Dimensions (HWD/cm):	32.4 x 19.1 x 22.9
Material of construction:	PVC
Form factors supported:	Tower, wall mountable with optional UPSWM accessory
Cooling method:	Convection
Battery Access:	Battery access door allows user replacement of UPS batteries
ENVIRONMENTAL	
Operating Temperature:	+32 to +104 degrees Fahrenheit 0 to +40 degrees Celsius
Operating Temperature: Storage Temperature:	-
	0 to +40 degrees Celsius +5 to +122 degrees Fahrenheit
Storage Temperature:	0 to +40 degrees Celsius +5 to +122 degrees Fahrenheit -15 to +50 degrees Celsius
Storage Temperature: Relative Humidity:	0 to +40 degrees Celsius +5 to +122 degrees Fahrenheit -15 to +50 degrees Celsius
Storage Temperature:  Relative Humidity:  COMMUNICATIONS	0 to +40 degrees Celsius +5 to +122 degrees Fahrenheit -15 to +50 degrees Celsius 0 to 95%, non-condensing  Built-in USB port supports on battery, low battery, power restored, AC line voltage, DC
Storage Temperature:  Relative Humidity:  COMMUNICATIONS  Network monitoring port:	0 to +40 degrees Celsius  +5 to +122 degrees Fahrenheit -15 to +50 degrees Celsius  0 to 95%, non-condensing  Built-in USB port supports on battery, low battery, power restored, AC line voltage, DC battery voltage and battery capacity messaging.
Storage Temperature:  Relative Humidity:  COMMUNICATIONS  Network monitoring port:  Software and cabling included:	0 to +40 degrees Celsius  +5 to +122 degrees Fahrenheit -15 to +50 degrees Celsius  0 to 95%, non-condensing  Built-in USB port supports on battery, low battery, power restored, AC line voltage, DC battery voltage and battery capacity messaging.  PowerAlert software available for free download at www.tripplite.com, includes USB cable.  Compatible with Tripp Lite's Watchdog system service to restore operation to locked equipment through soft reboot of application / OS or hard power off/on reboot of connected
Storage Temperature:  Relative Humidity:  COMMUNICATIONS  Network monitoring port:  Software and cabling included:  WatchDog compatibility:	0 to +40 degrees Celsius  +5 to +122 degrees Fahrenheit -15 to +50 degrees Celsius  0 to 95%, non-condensing  Built-in USB port supports on battery, low battery, power restored, AC line voltage, DC battery voltage and battery capacity messaging.  PowerAlert software available for free download at www.tripplite.com, includes USB cable.  Compatible with Tripp Lite's Watchdog system service to restore operation to locked equipment through soft reboot of application / OS or hard power off/on reboot of connected
Storage Temperature:  Relative Humidity:  COMMUNICATIONS  Network monitoring port:  Software and cabling included:  WatchDog compatibility:  LINE / BATTERY TRANSFER  Transfer time from line power to battery	0 to +40 degrees Celsius  +5 to +122 degrees Fahrenheit -15 to +50 degrees Celsius  0 to 95%, non-condensing  Built-in USB port supports on battery, low battery, power restored, AC line voltage, DC battery voltage and battery capacity messaging.  PowerAlert software available for free download at www.tripplite.com, includes USB cable.  Compatible with Tripp Lite's Watchdog system service to restore operation to locked equipment through soft reboot of application / OS or hard power off/on reboot of connected equipment - ideal for unattended kiosk applications
Storage Temperature:  Relative Humidity:  COMMUNICATIONS  Network monitoring port:  Software and cabling included:  WatchDog compatibility:  LINE / BATTERY TRANSFER  Transfer time from line power to battery mode:	to +40 degrees Celsius  +5 to +122 degrees Fahrenheit -15 to +50 degrees Celsius  0 to 95%, non-condensing  Built-in USB port supports on battery, low battery, power restored, AC line voltage, DC battery voltage and battery capacity messaging.  PowerAlert software available for free download at www.tripplite.com, includes USB cable.  Compatible with Tripp Lite's Watchdog system service to restore operation to locked equipment through soft reboot of application / OS or hard power off/on reboot of connected equipment - ideal for unattended kiosk applications  2-4 milliseconds  Switches to battery power as line voltage decreases to 99 volts or less. Resets back to line
Storage Temperature:  Relative Humidity:  COMMUNICATIONS  Network monitoring port:  Software and cabling included:  WatchDog compatibility:  LINE / BATTERY TRANSFER  Transfer time from line power to battery mode:  Low voltage transfer to battery power:	to +40 degrees Celsius  +5 to +122 degrees Fahrenheit -15 to +50 degrees Celsius  0 to 95%, non-condensing  Built-in USB port supports on battery, low battery, power restored, AC line voltage, DC battery voltage and battery capacity messaging.  PowerAlert software available for free download at www.tripplite.com, includes USB cable.  Compatible with Tripp Lite's Watchdog system service to restore operation to locked equipment through soft reboot of application / OS or hard power off/on reboot of connected equipment - ideal for unattended kiosk applications  2-4 milliseconds  Switches to battery power as line voltage decreases to 99 volts or less. Resets back to line power mode as line voltage increases to 104V or higher.
Storage Temperature:  Relative Humidity:  COMMUNICATIONS  Network monitoring port:  Software and cabling included:  WatchDog compatibility:  LINE / BATTERY TRANSFER  Transfer time from line power to battery mode:  Low voltage transfer to battery power:  High voltage transfer to battery power:	to +40 degrees Celsius  +5 to +122 degrees Fahrenheit -15 to +50 degrees Celsius  0 to 95%, non-condensing  Built-in USB port supports on battery, low battery, power restored, AC line voltage, DC battery voltage and battery capacity messaging.  PowerAlert software available for free download at www.tripplite.com, includes USB cable.  Compatible with Tripp Lite's Watchdog system service to restore operation to locked equipment through soft reboot of application / OS or hard power off/on reboot of connected equipment - ideal for unattended kiosk applications  2-4 milliseconds  Switches to battery power as line voltage decreases to 99 volts or less. Resets back to line power mode as line voltage increases to 104V or higher.
Storage Temperature:  Relative Humidity:  COMMUNICATIONS  Network monitoring port:  Software and cabling included:  WatchDog compatibility:  LINE / BATTERY TRANSFER  Transfer time from line power to battery mode:  Low voltage transfer to battery power:  High voltage transfer to battery power:  CERTIFICATIONS	0 to +40 degrees Celsius  +5 to +122 degrees Fahrenheit -15 to +50 degrees Celsius  0 to 95%, non-condensing  Built-in USB port supports on battery, low battery, power restored, AC line voltage, DC battery voltage and battery capacity messaging.  PowerAlert software available for free download at www.tripplite.com, includes USB cable.  Compatible with Tripp Lite's Watchdog system service to restore operation to locked equipment through soft reboot of application / OS or hard power off/on reboot of connected equipment - ideal for unattended kiosk applications  2-4 milliseconds  Switches to battery power as line voltage decreases to 99 volts or less. Resets back to line power mode as line voltage increases to 104V or higher.  Yes
Storage Temperature:  Relative Humidity:  COMMUNICATIONS  Network monitoring port:  Software and cabling included:  WatchDog compatibility:  LINE / BATTERY TRANSFER  Transfer time from line power to battery mode:  Low voltage transfer to battery power:  High voltage transfer to battery power:  CERTIFICATIONS  Certifications:	0 to +40 degrees Celsius  +5 to +122 degrees Fahrenheit -15 to +50 degrees Celsius  0 to 95%, non-condensing  Built-in USB port supports on battery, low battery, power restored, AC line voltage, DC battery voltage and battery capacity messaging.  PowerAlert software available for free download at www.tripplite.com, includes USB cable.  Compatible with Tripp Lite's Watchdog system service to restore operation to locked equipment through soft reboot of application / OS or hard power off/on reboot of connected equipment - ideal for unattended kiosk applications  2-4 milliseconds  Switches to battery power as line voltage decreases to 99 volts or less. Resets back to line power mode as line voltage increases to 104V or higher.  Yes

Product warranty:	2 year product warranty
Connected equipment insurance (USA and Canada Only):	\$200,000 connected equipment insurance (USA and Canada only)
SPECIAL FEATURES	
Cold Start:	Yes, inverter can be "cold started" to enable temporary AC output during a power failure
Appearance:	Attractive gray tower UPS

The policy of Tripp Lite is one of continuous improvement.

Specifications are subject to change without notice.

Therefore, your product may vary slightly from what is currently listed.



Tripp Lite World Headquarters 1111 W. 35th Street Chicago, IL 60609 USA

> Customer Support (773) 869-1234

© 2004 Tripp Lite. All Rights Reserved.