

SmartOnline Expandable Tower UPS System

On-line, double-conversion protection for mission critical applications



Model #: SU1000XLa

- ▶ 1000VA / 1kVA online, double-conversion, extended-run tower UPS
- ▶ Maintains sine-wave 120V +/-2% output during overvoltages to 138 and brownouts as low as 65V (50/60Hz auto-sensing)
- ▶ Simultaneous communications use via HID-compliant USB port, serial port, and SNMP/web card slot
- ▶ Fault tolerant auto-bypass mode, current monitoring and switched PDU control via 2 individually controllable load banks
- ▶ Input: NEMA 5-15P (120V 15A) / Output: 6 NEMA 5-15R (120V)
- ▶ 2 year product warranty / \$250,000 Ultimate Lifetime Insurance (USA, Puerto Rico & Canada only)

DESCRIPTION

Tripp Lite's Smart Online SU1000XLa on-line, double conversion UPS protects critical server, networking or telecommunications equipment from blackouts, brownouts, voltage fluctuations and surges in an attractive all-black upright tower form factor. Large capacity 1kVA / 800 watt UPS continuously converts incoming AC to DC, then back to perfect sine wave AC output at 120V AC (+/-2%). Removes harmonic distortion, fast electrical impulses, frequency fluctuations and other hard-to-solve power problems not addressed by other UPS systems. True sine wave output and zero transfer time offers guaranteed compatibility with all equipment types. Includes 6 UPS supported outlets. 2 single-outlet load banks can be independently controlled via a software interface to selectively reboot remote equipment, or automatically shed less critical loads to extend battery runtime for the most critical equipment. Battery support can be extended with the addition of an external battery pack (part# BP24V14 or BP24V34 limit one). Includes slot for internal SNMP/web card, plus DB9 enhanced serial monitoring port for unattended shutdown, remote control and monitoring of UPS system and power data. Network management interfaces support simultaneous communications via USB port, DB9 serial port and SNMPWEBCARD slot. HID-compliant USB interface enables integration with built-in power management and auto shutdown features of Windows and Mac OS X. Includes Tripp Lite's PowerAlert UPS Power Management Software. Compatible with Tripp Lite's Watchdog Service Monitoring/Rebooting Software.

KEY BUYING POINTS

- True on-line, double conversion UPS provides a constant, pure sine wave AC output
- Maintains continuous operation through blackouts, brownouts, voltage fluctuations and surges with zero transfer time
- Removes harmonic distortion, electrical impulses, frequency variations and other hard to solve power problems
- Accepts input voltages between 80 and 138 (65 to 138 at loads under 70%), regulating output to 120V AC +/-2%
- 1000VA / 800 watt output capacity with 6 total outlets (6 NEMA5-15R)
- Two built-in individually switchable load banks can be controlled via software interface to selectively reboot remote equipment or automatically shed less critical loads to extend battery runtime for the most critical equipment (2 banks of 1 outlet)
- Standard internal battery set provides 14 minutes runtime at half load and 4 minutes at full load
- Expandable runtime with an external battery pack (part# BP24V14 and BP24V34 limit one)
- Attractive all-black upright tower format
- Simultaneous communications use via HID-compliant USB port, serial port, and SNMP/web card slot
- HID-compliant USB interface enables integration with built-in power management and auto shutdown features of Windows and Mac OS X.
- DB9 serial network interface supports RS-232 and contact closure messaging
- Slot for optional SNMP/web card (part# SNMPWEBCARD)
- Included PowerAlert UPS Power Management Software and cabling provides monitoring of in-depth site power conditions, full UPS status and fault warnings, output load level and load bank power control
- Compatible with Tripp Lite's WatchDog Service Monitoring/Rebooting Software (part# WATCHDOGSW)
- Fault tolerant auto-bypass maintains continuous utility output to connected equipment, even in cases where the UPS is overloaded or suffers an internal failure that requires service
- Diagnostic LEDs

- \$250,000 Ultimate Lifetime connected equipment insurance (USA & Canada only)
- 2 year manufacturer's product warranty

TYPICAL APPLICATIONS

- Ideal for protection of critical 120V servers, networking equipment and sensitive electronics. Common applications include corporate or departmental servers, workstations, hubs, routers, bridges, CAD/CAM workstations, concentrators, IP telephony and traditional PBX switching systems.

OPTIONS & ACCESSORIES

- External battery packs: [BP24V14](#), [BP24V34](#)
- SNMP accessories: [SNMPWEBCARD](#), [ENVIROSENSE](#)
- AS400/iSeries Shutdown Cable Kit: [AS400 CABLE KIT](#)
- Dataline protectors: [DNET1](#), [DTEL2](#), [DCATV](#)
- Circuit Tester: [CT120](#)
- Power distribution: [PDU1215](#), [PS7224](#)
- Extended warranties: 3 Year [WEXT3-500-1500](#), 5 Year [WEXT5-500-1500](#)

PACKAGE INCLUDES

- SU1000XLa Online UPS System
- PowerAlert Software CD and cabling
- Owner's Manual with warranty information
- EPO (Emergency Power Off)cabling

COMPLETE SPECIFICATIONS

SYSTEM OVERVIEW

System overview:	On-line, double conversion tower UPS system
Voltage compatibility:	120V (100V, 110V) AC
Frequency compatibility:	50/60 Hz compatible

OUTPUT

Output volt amp capacity (VA):	1000
Output watt capacity (watts):	800
Output nominal voltage:	120V AC
Output voltage regulation:	Maintains full-time sine wave output within 2% of 120V, less than 5% total harmonic distortion
Output frequency regulation:	Regulates line frequency to 50/60Hz +/- 0.05Hz
Outlet quantity / type:	6 NEMA 5-15R
Customized load management receptacles:	"2 individually controllable single-outlet load banks support automated load shedding and remote reboot on demand of locked network devices. Configurable via PowerAlert software to automatically switch off optional loads, like monitors, to increase available runtime for servers and other critical devices. "
Overload protection:	Via 15A input breaker

INPUT

Maximum input amps:	8.6A
Input connection type:	NEMA 5-15P

Input cord length:	10 ft.
Recommended electrical service:	15A 120V

BATTERY

Full load runtime:	4.5 minutes
Half load runtime:	14 minutes
DC system voltage:	24VDC
Typical battery lifespan:	3-6 years, depending on usage
Battery recharge rate:	4-6 hours to 90%
Replacement Battery Cartridge:	RBC24-SUTWR

VOLTAGE REGULATION

Voltage regulation description:	On-line, double-conversion power conditioning maintains output within 2% of 120 volts at all times
Overvoltage correction:	Maintains output of 120V +/-2% during overvoltages to 138VAC
Brownout correction:	Maintains output of 120V +/-2% during undervoltages to 80VAC
Severe brownout correction:	Maintains output of 120V +/-2% during undervoltages to 65VAC (during load conditions of 70% or less)

LEDS ALARMS & SWITCHES

Front panel LEDs:	14 STATUS LEDs offer LINE POWER, ONLINE, BYPASS, ON BATTERY, OVERLOAD, BATTERY LOW, REPLACE BATTERY and FAULT status information. Also includes 4 LED meters for LOAD LEVEL / BATTERY LEVEL display (Battery level readout requires pressing "test" key)
Alarms:	Multi-function audible alarm offers notification of UPS start, backup operation, low battery warning, overload, UPS fault and remote shutdown
Switches:	Includes combination main power on/test and main power off switch

PHYSICAL

Shipping weight (lbs):	35.3
Shipping weight (kg):	16
Unit weight (lbs):	29.8
Unit weight (kg):	13.41
Unit Dimensions (HWD/in):	10 x 6.75 x 13.25
Unit Dimensions (HWD/cm):	25.4 x 17.1 x 33.7
Shipping Dimensions (HWD/in):	14.25 x 10 x 18.5
Shipping Dimensions (HWD/cm):	36.2 x 25.4 x 47
Material of construction:	Steel
Form factors supported:	Tower
Cooling method:	Fan
Battery Access:	Supports battery access and hot-swap replacement without powering connected equipment off

ENVIRONMENTAL

Operating Temperature:	+32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius
Storage Temperature:	+5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius
Relative Humidity:	0 to 95%, non-condensing

COMMUNICATIONS

Network monitoring port:	Includes USB and DB9 serial ports. Built-in DB9 port offers both enhanced RS-232 enabled monitoring data, plus contact closure monitoring ability. HID-compliant USB interface enables
---------------------------------	--

Software and cabling included:

integration with built-in power management and auto shutdown features of

Yes, includes PowerAlert software CD-ROM and complete cabling

SNMP compatibility:

Yes, includes slot for optional SNMPWEBCARD accessory (#SNMPWEBCARD)

WatchDog compatibility:

Yes, compatible with Tripp Lite's Watchdog system service to restore operation to locked equipment through soft reboot of applications / OS or hard power off/on reboot of connected equipment — ideal for unattended kiosk applications

LINE / BATTERY TRANSFER

Transfer time from line power to battery mode:

ZERO — online UPS continuously converts incoming AC to DC, then back to AC. When commercial power is interrupted, UPS maintains continuous output from battery reserves with absolutely no disruption in output AC power.

Low voltage transfer to battery power:

Maintains continuous operation during undervoltages as low as 80V (65V during load conditions of 70% or less). Below the switchover point, output is supported from battery derived AC power.

High voltage transfer to battery power:

Maintains continuous operation without using battery power during overvoltages to 138V. Above this point, output is supported from battery derived AC power.

CERTIFICATIONS

Certifications:

Tested to UL1778 (USA), CSA C22.2 No. 107.3 (Canada), Class B (emissions), FCC Part 68 / Industry Canada (telecommunications), RoHS-compliant

WARRANTY

Product warranty:

2 year product warranty

Connected equipment insurance (USA and Canada Only):

\$250,000 connected equipment insurance (USA and Canada only)

Optional coverage:

3-5 year warranties, plus next day and on-site warranty coverage available for select opportunities. Contact Tripp Lite for additional information.

SPECIAL FEATURES

EPO port:

Supports EPO (emergency power off) via included cabling

Cold Start:

Yes, inverter can be "cold started" to enable temporary AC output during a power failure

Appearance:

Attractive all-black tower housing

BATTERY PACK ACCESSORY (optional)

Battery Pack Accessory (optional):

BP24V14 or BP24V34 (limit one for both packs)

*The policy of Tripp Lite is one of continuous improvement.
Specifications are subject to change without notice.
Therefore, your product may vary slightly from what is currently listed.*



Tripp Lite World Headquarters
1111 W. 35th Street
Chicago, IL 60609 USA

Customer Support
(773) 869-1234

© 2007 Tripp Lite. All Rights Reserved.