

184-524

SEFRAM 5035
35 MHz analogue oscilloscope with Cursors and Readout

Sefram

Higher level performance and powerful facilities, can still be competitive in price.


Capabilities

- 35 MHz, dual channel
- Cursors/ Readout
- Probes x 10 / x1
- High sensitivity 1 mV/Div.
- TV, ALT triggering functions
- HOLD OFF function
- CH1 output

A unique standard of performance/price

The SEFRAM 5035 analogue oscilloscope features a 35 MHz bandwidth and a time-base range to 10 ns/div. Thanks to its READOUT function, you can display different parameters such as the horizontal and vertical sensitivity, the triggering mode,...

With the SEFRAM 5035 oscilloscope in your workstation, you will have the solution in terms of performance and price.



SEFRAM 5035

The SEFRAM 5035 is exceptionally easy to use. Its fine-line trace is matched by the clear and comprehensive readouts. The cursors provide precise measurement and direct screen readout of all amplitude and time domain values.

SEFRAM analogue oscilloscopes

The SEFRAM analogue oscilloscopes are your solution for your tests in laboratories, production facilities or educational workstation. Please see their specification in the following selection guide and choose the model that meets your needs.

	SEFRAM 5035	SEFRAM 5020	
Vertical system	Bandwidth	35 MHz	20 MHz
	Sensitivity	1 mV/Div.	1 mV/Div.
Horizontal system	Sweep time	(10 ns) 100 ns- 0.5 s/div.	(10 ns) 100 ns- 0.5 s/div.
	Expansion	x 10	x 10
Trigger	Modes	Auto-Level/ Auto/ Norm/ Single	Auto-Level/ Auto/ Norm/ Single
	Sources	CH1, CH2, ALT, Sect., Ext.	CH1, CH2, ALT, Sect., Ext.
	Coupling	DC, AC, HF Rej., TV-V, TV-H	DC, AC, HF Rej., TV-V, TV-H
Cursors		yes	
Readout		yes	

For any further information, please contact us on +33 (0) 4.77.59.01.01. In U.K., contact us on +44 (0) 1384.402731

TECHNICAL SPECIFICATION

SEFRAM 5035

VERTICAL SYSTEM	Sensitivity/ Accuracy	5 mV/ Div. - 5 V/ Div. / $\pm 3\%$
		1 mV/ Div. - 2 mV/ Div. / $\pm 5\%$
	Bandwidth	DC (AC 10 Hz) - 35 MHz (-3 dB)
		DC (AC 10 Hz) - 15 MHz (-3 dB) at 1 - 2 mV/ Div.
	Rise time	10 ns (25 ns at 1 mV - 2 mV/ Div.)
	Input impedance	1 M Ω $\pm 2\%$ // approx. 25 pF
	Input coupling mode	AC, DC, GND
	Polarity inversion	CH2
	Display mode	CH1, CH2, DUAL, ADD (ALT and CHOP automatic, CHOP lockable)
	CHOP frequency	Approx. 250 kHz
HORIZONTAL SYSTEM	CH1 output signal	≈ 50 mV/Div. into 50 Ω
	Sweep time/ Accuracy	0.1 μ s - 0.5 s/ Div. / $\pm 3\%$
		100 ns - 50 ms/Div. / $\pm 5\%$ (x 10 MAG)
TRIGGER		10 ns - 50 ns/Div. / $\pm 8\%$ (x 10 MAG)
	Modes	Auto-Level, AUTO, NORM, Single
	Trigger Source	CH1, CH2, ALT, LINE, EXT
	Trigger coupling	AC, DC, HF REJ, TV-V, TV-H
	Trigger slope	positive or negative
X-Y OPERATIONS	Hold-Off	variable > 2 screens
	Sensitivity/ Accuracy	1 mV - 5 V/ Div.; $\pm 4\%$
	Bandwidth	DC - 1 MHz
	Phase difference	< 3° (DC - 50 kHz)
Z AXIS	Sensitivity	> 3 Vp-p
	Input impedance	Approx. 5 k Ω
	Frequency response	DC - 5 MHz
CUSORS/ READOUT	Measurements	ΔV (for V, %, dB), ΔT , $1/\Delta T$, Phase, duty cycle, phase difference
		Taking the probe coefficient (x 1/ x 10) into account

GENERAL SPECIFICATION

SEFRAM 5035

Calibrator	1 kHz square wave, 2 Vp-p $\pm 2\%$	
CRT	Screen	15 cm rectangular, with internal graticule
	Accelerating voltage	8 x 10 DIV (1 Div. = 10 mm) 2.2 kV
Power source	AC 100V/ 120V/ 220V/ 230V $\pm 10\%$, 50/60 Hz, Approx. 70 VA (60 W _{max})	
Safety	IEC 1010, 300 V CAT. II	
Dimensions & Weight	310 x 150 x 455 mm; 8.2 kg	
Warranty	2 years	

SUPPLIED WITH

All SEFRAM 5035 oscilloscopes are supplied with a power cord and a user's manual.

OPTIONAL ACCESSORIES

- GE 1521 - Probe for oscilloscope (1/1, 1/10, 150 MHz)
- GE 3121 - Probe for oscilloscope (1/100, 200 MHz, 2 kV)
- GE 8100 - Differential Probe x 20/x 200
- SO 401 - BNC m./ 2 x BNC f. adaptor
- SO 402 - Isolated BNC m/ 2 x banana plugs
- SO 405 - 50 Ω , 2 W Load
- SO 410 - BNC/BNC cable (1m, noir)
- SP 280 - Current transducer for oscilloscope (100 mVAC+DC/1 AAC+DC, 30 A, \varnothing 19 mm, Bandwidth 100 kHz)

SP 280 - CURRENT TRANSDUCER

Current Ranges	20 AAC _{rms} / 30 Adc
Analog Output	100 mVAC+DC/1 AAC+DC
Accuracy	$\pm (1\% + 2 \text{ mA})$
Bandwidth	DC - 100 kHz
Max. jaw opening	\varnothing 19 mm
Power requirements	1 x 9 V (6F22)
Safety IEC 1010	300 V CAT. III / 600 V CAT. II

To discover the complete range of accessories, contact us and ask for the ELDITEST catalog

Specifications subject to change without notice - FT503500A/98

Sefram



SEFRAM
32, rue Edouard Martel - BP 55
42009 - St Etienne
Tel. +33 (0) 4.77.59.01.01
Fax. (33) 04.77.57.23.23
E-mail : Sefram.Stetienne@wanadoo.fr

Metrix Electronics plc
Mountfield House
659, High Street - Kingswinford
West Midlands - DY6 8AL
Tel. +44 (0) 1384 402731
Fax +44 (0) 1384 402732

For assistance and ordering

