

## Mini Pocket MultiMeter

Autoranging with 8 functions including Battery Test and EF (Electric Field) Test

### Features:

- Large 4000 count high contrast LCD display with bargraph
- Auto Power off to conserve battery life
- Autoranging with Data Hold and Range Hold
- EF Test (Electric Field), Battery Check, Diode Test and Continuity Beeper
- Built-in storage compartment for integrated test leads
- Over-range and low battery indication
- Designed to IEC1010, CAT II - 400V
- Complete with test leads and two LR44 button batteries

### Applications:

- Home wiring projects
- Testing electrical systems on cars and boats
- Hobby projects

**CAT II-400V**

Specifications	Range	Max. Resolution	Basic Accuracy (%rdg+digits)
DC Voltage:	400mV to 400V	100μV	±(1.5% + 2d)
AC Voltage:	400mV to 400V	100μV	±(2.0% + 5d)
DC Current:	400mA	0.1mA	±(2.0% + 4d)
Resistance:	400 to 40MΩ	0.1Ω	±(2.0% + 2d)
Diode Test:	0 to 2V DC Test Current at 1mA		
Continuity Test:	Audible beep <50Ω		
EF Test:	50 to 400VAC (50/60Hz)		
Battery Check:	1.5V Battery Check		
Power:	Two LR44 button batteries		
Dimensions:	0.75 x 4.6 x 2.8" (18 x 115 x 73mm)		

### Ordering Information:

**38109** .....Mini Pocket MultiMeter

**EXTECH INSTRUMENTS CORPORATION**

285 Bear Hill Road, Waltham, MA 02451-1064  
Phone: 781-890-7440 • FAX 781-890-7864

ISO 9001:2000 CERTIFIED

**"Make mine an Extech!"<sup>™</sup>**  
**www.extech.com**



07/12/05 - R1