





PTB 20144 6 Watts, 915–960 MHz Cellular Radio RF Power Transistor

Description

The 20144 is a class AB, NPN, common emitter RF power transistor intended for 25 Vdc operation from 915 to 960 MHz. Rated at 6 watts minimum output power, it may be used for both CW and PEP applications. Ion implantation, nitride surface passivation and gold metallization are used to ensure excellent device reliability. 100% lot traceability is standard.

- 6 Watts, 915–960 MHz
- Class AB Characteristics
- 50% Typ Collector Efficiency at 6 Watts
- Tested to solderability standards:
 - IEC-68-2-54
 - ANSI/J Std-002-A
- Gold Metallization
- Silicon Nitride Passivated



Maximum Ratings

Parameter	Symbol	Value	Unit
Collector-Emitter Voltage	V_{CER}	55	Vdc
Collector-Base Voltage	V_{CBO}	60	Vdc
Emitter-Base Voltage (collector open)	V_{EBO}	4.0	Vdc
Collector Current (continuous)	I_C	1.7	Adc
Total Device Dissipation at $T_{flange} = 25^\circ\text{C}$ Above 25°C derate by	P_D	22 0.125	Watts $\text{W}/^\circ\text{C}$
Storage Temperature Range	T_{stg}	-40 to +150	$^\circ\text{C}$
Thermal Resistance ($T_{flange} = 70^\circ\text{C}$)	$R_{\theta JC}$	8	$^\circ\text{C}/\text{W}$

Electrical Characteristics (100% Tested)


Characteristic	Conditions	Symbol	Min	Typ	Max	Units
Breakdown Voltage C to E	$I_B = 0\text{ A}, I_C = 50\text{ mA}$	$V_{(BR)CEO}$	24	30	—	Volts
Breakdown Voltage C to E	$V_{BE} = 0\text{ V}, I_C = 50\text{ mA}$	$V_{(BR)CES}$	60	70	—	Volts
Breakdown Voltage E to B	$I_C = 0\text{ A}, I_E = 5\text{ mA}$	$V_{(BR)EBO}$	3.5	5	—	Volts
DC Current Gain	$V_{CE} = 5\text{ V}, I_C = 1\text{ A}$	h_{FE}	20	50	120	—

RF Specifications (100% Tested)

Characteristic	Symbol	Min	Typ	Max	Units
Gain ($V_{CC} = 25\text{ Vdc}, P_{out} = 6\text{ W}, I_{CQ} = 50\text{ mA}, f = 960\text{ MHz}$)	G_{pe}	9	10	—	dB
Collector Efficiency ($V_{CC} = 25\text{ Vdc}, P_{out} = 6\text{ W}, I_{CQ} = 50\text{ mA}, f = 960\text{ MHz}$)	η_C	—	50	—	%
Load Mismatch Tolerance ($V_{CC} = 25\text{ Vdc}, P_{out} = 6\text{ W}, I_{CQ} = 50\text{ mA}, f = 960\text{ MHz}$ —all phase angles at frequency of test)	Ψ	—	—	30:1	—

Impedance Data (data shown for fixed-tuned broadband circuit)

($V_{CC} = 25\text{ Vdc}, P_{out} = 6\text{ W}, I_{CQ} = 50\text{ mA}$)



Frequency	Z Source		Z Load	
	R	jX	R	jX
915	2.5	-1.4	6.3	9.8
960	2.6	-0.8	7.0	12.4

