

SANYO

SB005-09SPA

Shottky Barrier Diode

90V, 50mA Rectifier

Applications

- High frequency rectification (switching regulators, converters and choppers).


Features

- Low forward voltage (V_F max=0.7V).
- Fast reverse recovery time (t_{rr} =10ns max).
- Low switching noise.
- Low leakage current and high reliability due to highly reliable planner structure.

Package Dimensions

unit:mm

1156



Specifications


Absolute Maximum Ratings at $T_a = 25^\circ\text{C}$

Parameter	Symbol	Conditions	Ratings	Unit
Repetitive Peak Reverse Voltage	V_{RRM}		-90	V
Non-repetitive Peak Reverse Surge Voltage	V_{RSM}		-95	V
Average Output Current	I_O	50Hz, resistive load, $T_a=102^\circ\text{C}$	50	mA
Surege Forward Current	I_{FSM}	50Hz sine wave, 1 cycle	2	A
Junction Temperature	T_j		-55 to +125	$^\circ\text{C}$
Storage Temperature	T_{stg}		-55 to +125	$^\circ\text{C}$






Electrical Characteristics at $T_a = 25^\circ\text{C}$

Parameter	Symbol	Conditions	Ratings			Unit
			min	typ	max	
Reverse Voltage	V_R	$I_R=-50\mu\text{A}$	-90			V
Forward Voltage	V_F	$I_F=-50\text{mA}$			0.7	V
Reverse Current	I_R	$V_R=-45\text{V}$			-15	μA
Interterminal Capacitance	C	$V_R=-10\text{V}$, $f=1\text{MHz}$		3.2		pF
Reverse Recovery Time	t_{rr}	$I_F=I_R=100\text{mA}$, $T_j=25^\circ\text{C}$, See specified Test Circuit.			10	ns
Thermal Resistance	R_{thj-a}			300		$^\circ\text{C/W}$

t_{rr} Test Circuit



SB005-09SPA



■ No products described or contained herein are intended for use in surgical implants, life-support systems, aerospace equipment, nuclear power control systems, vehicles, disaster/crime-prevention equipment and the like, the failure of which may directly or indirectly cause injury, death or property loss.

■ Anyone purchasing any products described or contained herein for an above-mentioned use shall:

- ① Accept full responsibility and indemnify and defend SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors and all their officers and employees, jointly and severally, against any and all claims and litigation and all damages, cost and expenses associated with such use:
- ② Not impose any responsibility for any fault or negligence which may be cited in any such claim or litigation on SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors or any of their officers and employees jointly or severally.

■ Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. SANYO believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.