

ACDC-620T**Digital 1000A AC/DC Clamp Multimeter****Technical data**

Display	LCD, 3-3/4-digit, 4000 Count
Mesaurement Ranges	
Current AC	0,1 A...1000 A
Tolerance	$\pm(2\% \text{ rdg.} + 5 \text{ Digits})$
Frequency Range	45 Hz...2 kHz
Current DC	0,1 A...1000 A
Tolerance	$\pm(1,5\% \text{ rdg.} + 3 \text{ Digits})$
Voltage AC	0,1 V...1000 V
Tolerance	$\pm(1,5\% \text{ rdg.} + 3 \text{ Digits})$
Frequency Range	45...400 Hz
Voltage DC	0,1 V...1000 V
Tolerance	$\pm(1\% \text{ rdg.} + 3 \text{ Digits})$
Continuity	$R < 10 \Omega$
Resistance	0,1 Ω ...1000 Ω
Tolerance	$\pm(1\% \text{ rdg.} + 3 \text{ Digits})$
Capacity	0,1 μF ...400 μF
Temperature	-40°C...1372°C
Jaw Opening	$\varnothing 52 \text{ mm}$
Pollution Degree	2
Overvoltage Category	CAT III/600 V
Safety	DIN VDE 0411, EN 61010, IEC 61010
Power Supply	1 x Battery 9 V, IEC 6LR61
Dimensions	32 x 64 x 260 mm
Weight	approx. 840 g