


**C-MOS QUAD SPST ANALOG SWITCH****■ GENERAL DESCRIPTION**

The NJU7301 is a quad break-before-make SPST analog switch protected up to 44V operating voltage.

Each switch is controlled by TTL or C-MOS compatible input.


**■ PACKAGE OUTLINE**

NJU7301D


NJU7301M

**■ FEATURES**

- High Break Down Voltage -- 44V
- Package Outline -- DIP/DMP 16
- C-MOS Technology

**6****■ PIN CONFIGURATION****■ TRUTH TABLE**

Logic (In)	Switch
0	ON
1	OFF

**■ EQUIVALENT CIRCUIT**

\* Logic input threshold voltage  $V_{TH}$  is about  $V^+ \times 0.128(V)$ .  
When the designing, enough margin is required.

**■ TERMINAL DESCRIPTION**

No.	SYMBOL	FUNCTION	No.	SYMBOL	FUNCTION
1	IN1	Control Signal Input	9	IN3	Control Signal Input
2	D1	Input/Output 1	10	D3	Input/Output 3
3	S1		11	S3	
4	V <sup>-</sup>	Negative (V <sup>-</sup> ) Power Supply	12	NC	Non Connection
5	GND	Ground	13	V <sup>+</sup>	Positive (V <sup>+</sup> ) Power Supply
6	S4	Input/Output 4	14	S2	Input/Output 2
7	D4		15	D2	
8	IN4	Control Signal Input	16	IN2	Control Signal Input

**6**

**■ ABSOLUTE MAXIMUM RATINGS**

( Ta=25°C )

P A R A M E T E R	S Y M B O L	R A T I N G S	U N I T
Supply Voltage	V <sup>+</sup> - V <sup>-</sup>	44	V
	V <sup>+</sup> - GND	19	
	GND - V <sup>-</sup>	25	
Input Voltage	V <sub>I</sub> , V <sub>S</sub> , V <sub>D</sub>	V <sup>-</sup> 0.5 ~ V <sup>+</sup> +0.5 *	V
Input Current	I <sub>I</sub>	30	mA
	I <sub>S</sub> , I <sub>D</sub> Continuous	20	
	Peak Value (PW=1ms, Duty0.1)	70	
Power Dissipation	P <sub>D</sub>	500 (DIP) 200 (DMP)	mW
Operating Temperature Range	T <sub>opr</sub>	0 ~ + 70	°C
Storage Temperature Range	T <sub>stg</sub>	- 65 ~ + 125	°C

\* V<sup>+</sup>+0.5V must be 44V or less.

**■ ELECTRICAL CHARACTERISTICS (DC CHARACTERISTICS)**

(  $V^+=15V$  ,  $V^-=-15V$  , GND=0V )

PARAMETER	SYMBOL	CONDITIONS	TYP	MAX			UNIT
			25°C	0°C	25°C	70°C	
Analog Signal Range	$V_{ANALOG}$		$\pm 15$		$\pm 15$	$\pm 15$	V
On-state Resistance	$R_{ON}$	$V_{IN}=0.8V$	$V_D=10V$	105	200	200	250
		$I_S=-1mA$	$V_D=-10V$	115	200	200	250
Source-off Leakage Current	$I_S(\text{off})$	$V_I=2.4V$	$V_S=14V, V_D=-14V$	0.01		5	100
			$V_S=-14V, V_D=14V$	-0.02		- 5	-100
Drain-off Leakage Current	$I_D(\text{off})$	$V_I=2.4V$	$V_D=14V, V_S=-14V$	0.01		5	100
			$V_D=-14V, V_S=14V$	-0.02		- 5	-100
Drain-on Leakage Current	$I_D(\text{on})$	$V_I=0.8V$	$V_D=V_S=14V$	0.1		5	200
			$V_D=V_S=-14V$	-0.15		- 5	-200
Input Current	$I_{IH}$	$V_I=2.4V$		-0.0004		- 1	- 10
		$V_I=15V$		0.003		1	10
Quiescent Current	$I^+$	$V_I=0V$		-0.0004		- 1	- 10
		$V_I=0 \text{ or } 2.4V$		0.9		2	
	$I^-$			-0.3		-1	



**■ SWITCHING CHARACTERISTICS**

(  $V^+=15V$  ,  $V^-=-15V$  , GND=0V )

PARAMETER	SYMBOL	CONDITIONS	TYP	MAX			UNIT
			25°C	0°C	25°C	70°C	
Turn-on Time	$t_{on}$	$R_L=1k\Omega$ , $C_L=35pF$	480		600		ns
Turn-off Time	$t_{off}$		370		450		
Charge Injection	$Q$	$C_L=1000pF$ , $V_{GEN}=0V$ , $R_{GEN}=0\Omega$	20				pC
Source-Off Capacit.	$C_s(\text{off})$	$f=100kHz$	$V_S=0V, V_I=5V$	5			pF
Drain-Off Capacit.	$C_D(\text{off})$		$V_D=0V, V_I=5V$	5			
Channel-On Capacitance	$C_D(\text{on})$ $+C_s(\text{on})$		$V_D=V_S=0V$ , $V_I=0V$	16			
Off Isolation	OIRR			70			
Channel-to-channel Crosstalk	CCRR	$V_S=2V_{P-P}$ , $R_L=75\Omega$		90			dB



## ■ MEASUREMENT CIRCUITS

### (1) Turn-on/Turn-off Time




6


### (2) Charge Injection



### (3) Off Isolation



### (4) Channel-To-Channel Crosstalk



# NJU7301

---

## MEMO

[CAUTION]  
The specifications on this databook are only given for information , without any guarantee as regards either mistakes or omissions. The application circuits in this databook are described only to show representative usages of the product and not intended for the guarantee or permission of any right including the industrial rights.